

Part No: TURBF-36M5ML

Band Pass Filters ,Center Frequency 36 MHz, Band Width 5MHz

电气特性 ELECTRICAL:

Parameter	Min.	Typ.	Max.	Units
Frequency range		36		MHz
Band Width			5	MHz
Insertion Loss(f0)			2.8	dB
Pass band Ripple			2.6	dB
VSWR			1.6	M v
Rejection	>40dB@fc±50Mhz			
Power Handing			2	Watts
Operating Temperature	-40		+70	°C
Impedance	50			Ohms
Input / Output Connector	SMA-Female			

外形尺寸Outline Drawing:

Unit: mm

